



**ELECTRONICS, INC.**  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089

## NTE15017 Integrated Circuit Head Amp Circuit for VCR

**Features:**

- The Function Consist of:  
     Video Signal Pre-Amplifier Circuit  
     Head Switchover Circuit  
     Drop-Out Compensation Circuit  
     RF AGC Circuit
- Low-Noise Head Amplifier
- Supply Voltage: 5V

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Supply Voltage,  $V_{CC}$  ..... 6V  
 Power Dissipation,  $P_D$  ..... 160mW  
 Operating Ambient Temperature Range,  $T_{opr}$  .....  $-20^\circ$  to  $+70^\circ\text{C}$   
 Storage Temperature Range,  $T_{stg}$  .....  $-40^\circ$  to  $+150^\circ\text{C}$

**Electrical Characteristics:** ( $V_{CC} = 5V$ ,  $T_A = +25^\circ\text{C}$  unless otherwise specified)

| Parameter                       | Symbol                        | Test Conditions   | Min   | Typ | Max  | Unit                |
|---------------------------------|-------------------------------|-------------------|-------|-----|------|---------------------|
| Circuit Current                 | $I_1$                         |                   | 8     | –   | 20   | mA                  |
| Channel 1 Gain                  | $G_{V4-10}$                   | $f = 1\text{MHz}$ | 52.5  | –   | 62.5 | dB                  |
| Channel 2 Gain                  | $G_{V8-10}$                   | $f = 1\text{MHz}$ | 52.5  | –   | 62.5 | dB                  |
| AGC Output Amplitude            | $V_{o(AGC\bullet 12)}$        | $f = 4\text{MHz}$ | 170   | –   | 330  | mV <sub>P-P</sub>   |
| AGC Control Sensitivity         | $\Delta V_{o(AGC\bullet 12)}$ | $f = 4\text{MHz}$ | –     | –   | 2.5  | dB                  |
| Output Amplifier Gain           | $G_{V13-17}$                  | $f = 4\text{MHz}$ | 0.05  | –   | 2.7  | dB                  |
| DOC Amplifier Gain              | $G_{V18-17}$                  | $f = 4\text{MHz}$ | 10.5  | –   | 14.0 | dB                  |
| DOC Sensitivity ON              | $S_{13-1}$                    | $f = 4\text{MHz}$ | –     | –   | –19  | dB                  |
| DOC Sensitivity OFF             | $S_{13-2}$                    | $f = 4\text{MHz}$ | –10.8 | –   | –    | dB                  |
| PG Input Sensitivity            | $S_2$                         |                   | –     | –   | 3    | V                   |
| Noise Voltage Referred to Input | $V_{ni1}$                     | 1MHz BPF          | –     | –   | 1    | $\mu\text{V}_{rms}$ |
|                                 | $V_{ni2}$                     | 1MHz BPF          | –     | –   | 1    | $\mu\text{V}_{rms}$ |

Note 1. Operating supply voltage range:  $V_{CCopr} = 4.5V$  to  $5.5V$ .

### Pin Connection Diagram

|                   |          |           |               |
|-------------------|----------|-----------|---------------|
| V <sub>CC</sub>   | <b>1</b> | <b>18</b> | DOC Amp Input |
| PG Input          | <b>2</b> | <b>17</b> | FM Output     |
| Damping (1)       | <b>3</b> | <b>16</b> | DOC Detect    |
| FM Input (1)      | <b>4</b> | <b>15</b> | DOC Pulse     |
| GND               | <b>5</b> | <b>14</b> | GND           |
| FM Input (2)      | <b>6</b> | <b>13</b> | DOC Input     |
| Damping (2)       | <b>7</b> | <b>12</b> | FM Equalizer  |
| Reference Voltage | <b>8</b> | <b>11</b> | FM Output     |
| AGC Detect        | <b>9</b> | <b>10</b> | Chroma Output |

