



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1851 Integrated Circuit Audio Amplifier, 24W BTL

Description:

The NTE1851 is a monolithic integrated class-B amplifier in a 13-Lead Staggered SIP type package primarily developed for car radio applications, and also to drive low-impedance loads (down to 1.6Ω). At a supply voltage $V_{CC} = 14.4V$, an output power of 21W can be delivered into a 4Ω BTL (Bridge-Tied Load), or, when used as a stereo amplifier, it delivers 2 x 11W into 2Ω or 2 x 6.5W into 4Ω.

Features:

- Flexibility In Use – Mono BTL as well as Stereo
- High Output Power
- Low Offset Voltage at the Output (Important for BTL)
- Large Usable Gain Variation
- Very Good Ripple Rejection
- Internal Limited Bandwidth for High Frequencies
- Low Standby Current Possibility (1μA Typ), to Simplify Required Switches: TTL Drive Possible
- Low Number of Small-Sized External Components
- High Reliability
- Load Dump Protection
- AC and DC Short-Circuit Safe to Ground up to $V_{CC} = 18V$
- Thermal Protection
- Speaker Protection in Bridge Configuration
- SOAR Protection
- Outputs Short-Circuit Safe to Ground in BTL
- Reverse-Polarity Safe

Applications:

- Car Radio Applications
- Drive Low Impedance Loads
- Stereo Amplifier

Absolute Maximum Ratings:

Supply Voltage (Pin10), V_{CC}	
Operating	18V
Non-Operating	28V
Supply Voltage (During 50ms Load Dump Protection), V_{CC}	45V
Peak Output Current, I_{OM}	8A
Crystal Temperature, T_C	+150°C
Storage Temperature Range, T_{stg}	-65° to +150°C
AC and DC Short-Circuit Safe Voltage	18V
Reverse Polarity	10V

DC Electrical Characteristics:

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Supply Voltage Range (Pin10)	V_{CC}		6	–	18	V
Repetitive Peak Output Current	I_{ORM}		–	–	4	A
Total Quiescent Current	I_{TOT}		–	75	75	mA
Switching Level 11 OFF	V_{11}		–	–	1.8	V
ON			3.0	–	–	V
Impedance Between Pin10 & Pin6; Pin10 & Pin8	$ Z_{OFF} $	Standby Position $V_{11} < 1.8V$	100	–	–	k Ω
Standby Current	I_{SB}	$V_{11} = 0$ to 0.8V	–	1	100	μA
Switch-On Current (Pin11)	I_{SO}	$V_{11} \leq V_{10}$	–	10	100	μA

AC Electrical Characteristics: ($T_A = +25^\circ C$, $V_{CC} = 14.4V$, $f = 1kHz$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Bridge-Tied Load Application (BTL)							
Output Power with Bootstrap	P_O	$R_L = 4\Omega$	$V_{CC} = 14.4V$, $d_{TOT} = 0.5\%$	15.5	18.0	–	W
			$V_{CC} = 14.4V$, $d_{TOT} = 10\%$	20	24	–	W
			$V_{CC} = 13.2V$, $d_{TOT} = 0.5\%$	–	15	–	W
			$V_{CC} = 13.2V$, $d_{TOT} = 10\%$	–	20	–	W
Open-Loop Voltage Gain	G_O		–	75	–	dB	
Closed-Loop Voltage Gain	G_C	Note 2	–	40	–	dB	
Output Power without Bootstrap	P_O	Note 3	$V_{CC} = 14.4V$, $d_{TOT} = 0.5\%$	–	12	12	W
			$V_{CC} = 14.4V$, $d_{TOT} = 10\%$	–	15	15	W
			$V_{CC} = 13.2V$, $d_{TOT} = 0.5\%$	–	9	9	W
			$V_{CC} = 13.2V$, $d_{TOT} = 10\%$	–	12	12	W
Frequency Response at –3dB	B	Note 4	20	–	20	Hz	
Input Impedance	$ Z_i $	Note 5	1	–	–	M Ω	
Noise Input Voltage (RMS Value)	$V_{N(RMS)}$	$R_S = 0\Omega$	f = 20Hz to 20kHz	–	0.2	0.2	mV
		$R_S = 10k\Omega$		–	0.35	0.35	mV
	V_N	–		0.25	0.8	mV	
Supply Voltage Ripple Rejection	RR	f = 100Hz	42	50	50	dB	
DC Output Offset Voltage Between the Outputs	$ \Delta V_{5-9} $		–	2	50	mV	
Loudspeaker Protection (All Conditions) Maximum DC Voltage (Across the Load)	$ \Delta V_{5-9} $		–	–	1	V	
Power Bandwidth	B	–1dB, $d_{TOT} = 0.5\%$	30	–	40	kHz	

Note 1. The internal circuit impedance at Pin11 is $> 5k\Omega$ if $V_{11} > V_{10}$.

Note 2. Closed-Loop voltage gain can be chosen between 32 and 56dB (BTL), and is determined by external components.

Note 3. Without the bootstrap the 100 μF capacitor between Pin5 and Pin6 (Pin8 and Pin9) can be omitted. Pin6, Pin8, and Pin10 have to be interconnected.

Note 4. Frequency response externally fixed.

Note 5. The input impedance in the test circuit is typically 100k Ω .

AC Electrical Characteristics (Cont'd): ($T_A = +25^\circ\text{C}$, $V_{CC} = 14.4\text{V}$, $f = 1\text{kHz}$ unless otherwise specified)

Parameter	Symbol	Test Conditions		Min	Typ	Max	Unit
Stereo Application							
Output Power with Bootstrap	P_O	$d_{TOT} = 10\%$ Note 6	$V_{CC} = 14.4\text{V}$, $R_L = 4\Omega$	6	7	-	W
			$V_{CC} = 14.4\text{V}$, $R_L = 2\Omega$	10	12	-	W
			$V_{CC} = 13.2\text{V}$, $R_L = 4\Omega$	-	6	-	W
			$V_{CC} = 13.2\text{V}$, $R_L = 4\Omega$	-	10	-	W
Output Power with Bootstrap	P_O	$d_{TOT} = 0.5\%$ Note 6	$V_{CC} = 14.4\text{V}$, $R_L = 4\Omega$	-	5.5	-	W
			$V_{CC} = 14.4\text{V}$, $R_L = 2\Omega$	-	9.0	-	W
			$V_{CC} = 13.2\text{V}$, $R_L = 4\Omega$	-	4.5	-	W
			$V_{CC} = 13.2\text{V}$, $R_L = 4\Omega$	-	7.5	-	W
Output Power without Bootstrap	P_O	$d_{TOT} = 10\%$, $V_{CC} = 14.4\text{V}$, $R_L = 4\Omega$, Note 3, Note 6, & Note 7		-	6	-	W
Frequency Response at -3dB	B	Note 4		40	-	20	kHz
Supply Voltage Ripple Rejection	RR	Note 8		-	50	-	dB
Channel Separation	α	$R_S = 10\text{k}\Omega$, $f = 1\text{kHz}$		40	50	-	dB
Closed-Loop Voltage Gain	G_C	Note 9		-	40	-	dB
Noise Input Voltage (RMS Value)	$V_{N(RMS)}$	$R_S = 0\Omega$	$f = 20\text{Hz to } 20\text{kHz}$	-	0.15	-	mV
		$R_S = 10\text{k}\Omega$		-	0.25	-	mV
	V_N	-		0.2	-	mV	

Note 1. The internal circuit impedance at Pin11 is $> 5\text{k}\Omega$ if $V_{11} > V_{10}$.

Note 2. Closed-Loop voltage gain can be chosen between 32 and 56dB (BTL), and is determined by external components.

Note 3. Without the bootstrap the $100\mu\text{F}$ capacitor between Pin5 and Pin6 (Pin8 and Pin9) can be omitted. Pin6, Pin8, and Pin10 have to be interconnected.

Note 4. Frequency response externally fixed.

Note 5. The input impedance in the test circuit is typically $100\text{k}\Omega$.

Note 6. Output power is measured directly at the output pins of the IC.

Note 7. A resistor of $56\text{k}\Omega$ between Pin3 and Pin7 to reach symmetrical clipping.

Note 8. Supply voltage ripple rejection measured with a source impedance of 0Ω (Maximum ripple amplitude: 2V).

Note 9. Closed-Loop voltage gain can be chosen between 26 and 50dB (Stereo), and is determined by external components.

Pin Connection Diagram
(Front View)

