



ELECTRONICS, INC.  
44 FARRAND STREET  
BLOOMFIELD, NJ 07003  
(973) 748-5089  
<http://www.nteinc.com>

## NTE1015 Integrated Circuit Low Noise AF Preamplifier Hybrid Module

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Maximum Supply Voltage, $V_{CC\text{max}}$	20V
Maximum Supply Current, $I_{CC\text{max}}$	20mA
Maximum Power Dissipation, $P_{d\text{max}}$	300mW
Operating Temperature Range, $T_{opr}$	$-20^\circ$ to $+80^\circ\text{C}$
Storage Temperature Range, $T_{stg}$	$-20^\circ$ to $+100^\circ\text{C}$

**Recommended Operating Conditions:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Supply Voltage, $V_{CC}$	15V
--------------------------	-----

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$ ,  $V_{CC} = 15\text{V}$ ,  $V_{in} = 2\text{mV}$ ,  $f = 1\text{kHz}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Output Voltage	$V_O$		0.42	—	0.90	V
Distortion	KF		—	—	3.0	%

**Pin Connection Diagram  
(Front View)**

