



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE158 Germanium PNP Transistor Audio Power Amplifier

**Description:**

The NTE158 is a germanium PNP triode transistor in a TO1 type package designed for low-power, large signal audio applications.

**Absolute Maximum Ratings:** ( $T_A = +25^\circ\text{C}$ )

|  |                                    |
|--|------------------------------------|
| Collector-Base Voltage, $V_{CBO}$ .....  | 32V                                |
| Collector-Emitter Voltage ( $R_{BE} \leq 500\pm$ ), $V_{CER}$ .....                    | 32V                                |
| Emitter-Base Voltage, $V_{EBO}$ .....  | 10V                                |
| Collector Current, $I_C$ .....   | 1A                                 |
| Base Current, $I_B$ .....  | 40mA                               |
| Power Dissipation ( $T_A = +25^\circ\text{C}$ ), $P_C$ .....                           | 550mW                              |
| Derate Above $25^\circ\text{C}$ .....  | 0.3mW/ $^\circ\text{C}$            |
| Storage Temperature Range, $T_{stg}$ .....   | $-55^\circ$ to $+90^\circ\text{C}$ |
| Lead Temperature (During Soldering, 1/16" $\pm$ 1/32" from case for 5sec), $T_L$ ..... | $+245^\circ\text{C}$               |

**Electrical Characteristics:** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

| Parameter                                 | Symbol        | Test Conditions                         | Min | Typ | Max | Unit     |
|---|---------------|---|-----|-----|-----|----------|
| Collector-Base Breakdown Voltage          | $V_{(BR)CBO}$ | $I_C = 200\leq A, I_E = 0$              | 32  | -   | -   | V        |
| Emitter-Base Breakdown Voltage            | $V_{(BR)EBO}$ | $I_E = 200\leq A, I_C = 0$              | 10  | -   | -   | V        |
| Collector Cutoff Current                  | $I_{CBO}$     | $V_{CB} = -10V, I_E = 0$                | -   | -   | 10  | $\leq A$ |
| Emitter Cutoff Current                    | $I_{EBO}$     | $V_{EB} = -5V, T_J = +75^\circ\text{C}$ | -   | -   | 500 | $\leq A$ |
| DC Current Gain                           | $h_{FE}$      | $V_{CB} = 1V, I_C = 300mA$              | 50  | 90  | 175 |          |
| Base-Emitter Voltage                      | $V_{BE}$      | $V_{CE} = 1V, I_C = 300mA$              | 280 | -   | 600 | mV       |
| Forward Current Transfer Cutoff Frequency | $f_{hfe}$     |   | 10  | -   | 20  | kc       |
| Output Capacitance                        | $C_{ob}$      | $V_{CB} = -5V, I_E = 0 @ 0.45mc$        | 80  | -   | 105 | pF       |

