



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE7237 Integrated Circuit 3-Terminal Adjustable Current Source TO-92 Type Package

Description:

The NTE7237 is a 3-terminal adjustable current source in a TO-92 type package featuring 10,000:1 range in operating current, excellent current regulation and a wide dynamic voltage range of 1V to 40V. Current is established with one external resistor and no other parts are required. Initial current accuracy is $\pm 3\%$. This device is a true floating current source with no separate power supply connections. In addition, reverse applied voltages of up to 20V will draw only a few dozen microamperes of current, allowing the device to act as both a rectifier and current source in AC applications.

The sense voltage used to establish operating current in the NTE7237 is 64mV at +25°C and is directly proportional to absolute temperature (°K). The simplest one external resistor connection, then, generates a current with $\approx +0.33\%/^{\circ}\text{C}$ temperature dependence. Zero drift operation can be obtained by adding one extra resistor and a diode.

Applications for the current sources include bias networks, surge protection, low power reference, ramp generation, LED driver, and temperature sensing.

The NTE7237 is guaranteed over a temperature range of 0° to +70°C.

Features:

- Operates From 1V to 40V
- 0.02%/V Current Regulation
- Programmable from 1 μ A to 10mA
- True 2-Terminal Operation
- $\pm 3\%$ Initial Accuracy

Absolute Maximum Ratings:

V+ to V- Forward Voltage	40V
V+ to V- Reverse Voltage	20V
R Pin to V- Voltage	5V
Set Current	10mA
Power Dissipation	400mW
ESD Susceptibility (Note 1)	2000V
Operating Temperature Range (Note 2), T _{opr}	0° to +70°C
Thermal Resistance, Junction-to-Ambient, R _{thJA}	
0.4" Leads	180°C/W
0.125" Leads	160°C/W
Lead Temperature (During Soldering, 10sec), T _L	+260°C

Note 1. Human body model, 100pF discharge through a 1.5k Ω resistor.

Note 2. For elevated temperature operation, T_{jmax} is +100°C.



Electrical Characteristics: (Note 3)

Parameter	Test Conditions	Min	Typ	Max	Unit	
Set Current Error	$V_+ = 2.5V$, Note 4	$10\mu A \leq I_{SET} \leq 1mA$	-	-	6	%
		$1mA \leq I_{SET} \leq 5mA$	-	-	8	%
		$2\mu A \leq I_{SET} \leq 10\mu A$	-	-	12	%
Ratio of Set Current to Bias Current	$100\mu A \leq I_{SET} \leq 1mA$	14	18	26		
	$1mA \leq I_{SET} \leq 5mA$	-	14	-		
	$2\mu A \leq I_{SET} \leq 100\mu A$	-	18	26		
Minimum Operating Voltage	$2\mu A \leq I_{SET} \leq 100\mu A$	-	0.8	-	V	
	$100\mu A \leq I_{SET} \leq 1mA$	-	0.9	-	V	
	$1mA \leq I_{SET} \leq 5mA$	-	1.0	-	V	
Average Change in Set Current with Input Voltage	$2\mu A \leq I_{SET} \leq 1mA$	$1.5V \leq V_+ \leq 5V$	-	0.02	0.1	%/V
		$5V \leq V_+ \leq 40V$	-	0.01	0.05	%/V
	$1mA \leq I_{SET} \leq 5mA$	$1.5V \leq V_+ \leq 5V$	-	0.03	-	%/V
		$5V \leq V_+ \leq 40V$	-	0.02	-	%/V
Temperature Dependence of Set Current	$25\mu A \leq I_{SET} \leq 1mA$, Note 5	0.96T	T	1.04T		
Effective Shunt Capacitance		-	15	-	pF	

Note 3. Unless otherwise specified, tests are performed at $T_J = +25^\circ C$ with pulse testing so that junction temperature does not change during test.

Note 4. Set current is the current flowing into the V_+ pin. For the Basic 2-Terminal Current Source circuit, I_{SET} is determined by the following formula: $I_{SET} = 67.7mV/R_{SET}$ (@ $+25^\circ C$). Set current error is expressed as a percent deviation from this amount. I_{SET} increases at $0.336\%/C$ at $T_J = +25^\circ C$ ($227\mu V/^\circ C$)

Note 5. I_{SET} is directly proportional to absolute temperature ($^\circ K$). I_{SET} at any temperature can be calculated from: $I_{SET} = I_o(T/T_o)$ where I_o is I_{SET} measured at T_o ($^\circ K$).



