



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089

TIP106 Silicon PNP Transistor Darlington Power Amp, Switch TO-220 Type Package

Description:

The TIP106 is a silicon PNP Darlington transistor in a TO-220 type package designed for general purpose amplifier and low-speed switching applications.

Features:

- High DC Current Gain: $h_{FE} = 2500$ (Typ) at $I_C = 4A$
- Collector-Emmitter Sustaining Voltage: $V_{CEO(sus)} = 80V$ (Min) at $I_C = 30mA$
- Low Collector-Emmitter Saturation Voltage: $V_{CE(sat)} = 2V$ (Max) at $I_C = 3A$
 $V_{CE(sat)} = 2.5V$ (Max) at $I_C = 8A$

Absolute Maximum Ratings: (Note 1)

Collector-Emmitter Voltage, V_{CEO}	80V
Collector-Base Voltage, V_{CB}	80V
Emitter-Base Voltage, V_{EB}	5V
Collector Current, I_C	
Continuous	8A
Peak	15A
Base Current, I_B	1A
Total Power Dissipation ($T_C = +25^\circ C$), P_D	80W
Derate Above $+25^\circ C$	0.64W/ $^\circ C$
Unclamped Inductive Load Energy (Note 2), E	30mJ
Total Power Dissipation ($T_A = +25^\circ C$), P_D	2.0W
Derate Above $+25^\circ C$	0.016W/ $^\circ C$
Operating Junction Temperature Range, T_J	-65° to $+150^\circ C$
Storage Temperature Range, T_{stg}	-65° to $+150^\circ C$
Thermal Resistance, Junction-to-Case, R_{thJC}	1.56 $^\circ C/W$
Thermal Resistance, Junction-to-Ambient, R_{thJA}	62.5 $^\circ C/W$

Note 1. Stresses exceeding those listed in the Absolute Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damages may occur and reliability may be affected.

Note 2. $I_C = 1.1A$, $L = 50mH$, P.R.F. = 10Hz, $V_{CC} = 20V$, $R_{BE} = 100\Omega$.

Electrical Characteristics: ($T_C = +25^\circ\text{C}$ unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
OFF Characteristics						
Collector–Emitter Sustaining Voltage	$V_{CEO(sus)}$	$I_C = 30\text{mA}, I_B = 0$, Note 3	80	–	–	V
Collector Cutoff Current	I_{CBO}	$V_{CB} = 80\text{V}, I_E = 0$	–	–	50	μA
	I_{CEO}	$V_{CE} = 40\text{V}, I_B = 0$	–	–	50	μA
Emitter Cutoff Current	I_{EBO}	$V_{BE} = 5\text{V}, I_C = 0$	–	–	8	mA
ON Characteristics (Note 3)						
DC Current Gain	h_{FE}	$V_{CE} = 4\text{V}, I_C = 3\text{A}$	1000	–	20,000	
		$V_{CE} = 4\text{V}, I_C = 8\text{A}$	200	–	–	
Collector–Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = 3\text{A}, I_B = 6\text{mA}$	–	–	2.0	V
		$I_C = 8\text{A}, I_B = 80\text{mA}$,	–	–	2.5	V
Base–Emitter On Voltage	$V_{BE(on)}$	$I_C = 8\text{A}, V_{CE} = 4\text{V}$	–	–	2.8	V
Dynamic Characteristics						
Small–Signal Current Gain	h_{fe}	$I_C = 3\text{A}, V_{CE} = 4\text{V}, f = 1\text{MHz}$	4.0	–	–	
Output Capacitance	C_{ob}	$V_{CB} = 10\text{V}, I_E = 0, f = 0.1\text{MHz}$	–	–	300	pF

Note 3. Pulse Test: Pulse Width $\leq 300\mu\text{s}$, Duty Cycle $\leq 2\%$.

