



**ELECTRONICS, INC.**  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089

## NTE1895 Integrated Circuit Hybrid Switching Voltage Regulator

**Absolute Maximum Ratings:**

Maximum Peak Input Voltage, $V_{IN}$ .....	550V
Input Current, $I_{IN}$	
Continuous .....	10A
Pulse .....	20A
Maximum Output Current ( $V_O = 115V$ ), $I_O$ .....	1.4A
Power Dissipation ( $T_C = +100^\circ C$ ), $P_D$ .....	27W
Power Transistor Junction Temperature, $T_J$ .....	+150°C
Operating Temperature Range (Case Temperature, Note 1), $T_{opr}$ .....	-20° to +125°C
Storage Temperature Range, $T_{stg}$ .....	-30° to +125°C

Note 1. Recommended Operating Temperature:  $T_{opr} = +100^\circ C$

**Electrical Characteristics:** ( $T_A = +25^\circ C$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Output Voltage	$V_O$	$V_{IN} = 120V, I_O = 1.1A$ , Note 2	108.5	110.0	111.5	V
Set Output Voltage	$V_O$	$I_{IN} = 7mA$	41.3	41.8	42.3	V
Line Regulation	$Reg_{LINE}$	$V_{IN} = 90V$ to $145V, I_O = 1.1A$	Initial Value $\pm 1V$			V
Load Regulation	$Reg_{LOAD}$	$V_{IN} = 120V, I_O = 0.6A$ to $1.1A$	Initial Value $\pm 2V$			V
Output Voltage Temperature Coefficient	$K_t$	$T_C = -20^\circ$ to $+100^\circ C, I_{IN} = 7mA$	-	$\pm 2$	-	mV/°C
Saturation Voltage	$V_{CE(sat)}$	$I_C = 5A, I_B = 1A$	-	-	0.5	V
	$V_{BE(sat)}$	$I_C = 5A, I_B = 1A$	-	-	1.5	V
DC Current Gain	$h_{FE}$	$I_C = 1A, V_{CE} = 4V$	15	-	40	
Collector Cutoff Current	$I_{CEX}$	$V_{CE} = 550V, V_{BE} = 1.5V$	-	-	1	A
Power Transistor Thermal Resistance	$R_{\theta JC}$	Between Junction and Case	-	1.8	-	°C/W
Switching Time	$t_s$		-	-	12.0	$\mu s$
	$t_f$		-	-	0.7	$\mu s$

Note 2. Output voltage is determined by the ratio between the sensing winding “D” and the secondary winding “S”.

**Pin Connection Diagram**  
(Front View)

