



ELECTRONICS, INC.
 44 FARRAND STREET
 BLOOMFIELD, NJ 07003
 (973) 748-5089
<http://www.nteinc.com>

NTE1518 Integrated Circuit AM RF/IF Detector, AGC

Description:

The NTE1518 is an integrated circuit for AM tuners. It is suitable for use in automotive radio receivers, where compact mounting is required. Internally, RF amplifier, mixer, IF amplifier, detector and two types of AGC circuit are included.

Features:

- Reduction of adjustment time and mounting area for IF transformer
- Balanced at all frequencies
- Good S/N and Tweet Characteristic
- Protection Against Electrostatic Damage at the Antenna Terminal
- No Clicks When Power Switch is Turned On
- Wide AGC Range is Provided by two AGC Circuits Employed in the IF and RF Stages
- Can Withstand Large Input and High S/N

Absolute Maximum Ratings: ($T_A = +25^\circ\text{C}$ unless otherwise specified)

Supply Voltage, V_{CC} 18V
 Input Voltage, V_i 7Vp-p
 Power Dissipation ($T_A = 75^\circ\text{C}$), P_D 430mW
 Operating Temperature Range, T_{opr} -30° to $+75^\circ\text{C}$
 Storage Temperature Range, T_{stg} -40° to $+125^\circ\text{C}$

Electrical Characteristics: ($T_A = +25^\circ\text{C}$, $V_{CC} = 13\text{V}$, $f = 1\text{MHz}$, $f_{mod} = 400\text{Hz}$, $\text{MOD} = 20\%$, $R_L = 10\text{k}\Omega$)

Parameter	Test Conditions	Rating	Unit	
Max. Sensitivity	Input Voltage at which Det Output Voltage = 40mV_{rms}	13	$\text{dB}\mu\text{V}$	
Useable Sensitivity	Input Voltage at which S/N is 20dB	23	$\text{dB}\mu\text{V}$	
Detector Output	$v_i = 74\text{dB}\mu\text{V}$	110	mV_{rms}	
Detector Distortion		0.4	%	
Signal-to-Noise Ratio		54	dB	
Overload Distortion	$v_i = 126\text{dB}\mu\text{V}$	0.4	%	
IF Rejection	$f = 1\text{MHz}$, $v_o = 40\text{mV}_{rms}$, IF-450kHz	72	dB	
Image Rejection	$f = 1\text{MHz}$, $v_o = 40\text{mV}_{rms}$, $f + 2\text{IF}$	74	dB	
Selectivity	$f = 1\text{MHz}$, $\Delta f = \pm 10\text{kHz}$	45	dB	
Tweet	$v_i = 74\text{dB}\mu\text{V}$	2IF = 900kHz	45	dB
		3IF = 1350kHz	50	dB

Pin Connection Diagram

19	V _{CC}
18	AGC Detector Input
17	Bypass
16	Bypass
15	Detector Output
14	Detector Input
13	Bypass
12	IF Output
11	IF Input
10	GND
9	GND
8	Local OSC
7	Mixer Output
6	Mixer Input
5	Bypass
4	RF Output
3	Bypass
2	Bypass
1	RF Input

