



ELECTRONICS, INC.  
 44 FARRAND STREET  
 BLOOMFIELD, NJ 07003  
 (973) 748-5089  
<http://www.nteinc.com>

## NTE1117 Integrated Circuit Audio Power Amp, 2 Watt

**Description:**

The NTE1117 is a monolithic integrated audio amplifier in a 14-Lead DIP type plastic package designed for use as a low frequency class B amplifier with a wide range of supply voltage of 3V to 16V.

**Features:**

- Minimum Working Voltage of 3V
- Low Quiescent Current
- Low Number of External Components
- Good Ripple Rejection
- No Cross-Over Distortion
- Output Power:
  - $P_O = 2W$  at 12V – 8Ω
  - $P_O = 1.6W$  at 9V – 4Ω
  - $P_O = 1.2W$  at 9V – 8Ω

**Absolute Maximum Ratings:**

Supply Voltage, $V_S$ .....	16V
Output Peak Current, $I_O$ .....	1.5A
Power Dissipation ( $T_A = +50^\circ C$ ), $P_{tot}$ .....	1.25W
Operating Junction Temperature Range, $T_J$ .....	-40° to 150°C
Storage Temperature Range, $T_{stg}$ .....	-40° to 150°C
Thermal Resistance, Junction-to-Ambient, $R_{thJA}$ .....	80°C/W

**Electrical Characteristics:** ( $T_A = +25^\circ C$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Supply Voltage	$V_S$		3	-	16	V	
Quiescent Output Voltage (Pin12)	$V_O$	$V_S = 9V$	4	4.5	5	V	
Quiescent Drain Current	$I_d$	$V_S = 9V$	-	4	-	mA	
Bias Current (Pin7)	$I_b$	$V_S = 9V$	-	0.1	-	μA	
Output Power	$P_O$	d = 10%, f = 1kHz, R <sub>f</sub> = 120Ω	$V_S = 12V, R_L = 8\Omega$	-	2	-	W
			$V_S = 9V, R_L = 4\Omega$	-	1.6	-	W
			$V_S = 9V, R_L = 8\Omega$	-	1.2	-	W
			$V_S = 6V, R_L = 4\Omega$	-	0.75	-	W
			$V_S = 3.5V, R_L = 4\Omega$	-	0.22	-	W

**Electrical Characteristics (Cont'd):** ( $T_A = +25^\circ\text{C}$  unless otherwise specified)

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit	
Input Sensitivity	$V_{i(\text{rms})}$	$P_O = 1.2\text{W}, V_S = 9\text{V}, f = 1\text{kHz}, R_L = 8\Omega$	$R_f = 33\Omega$	-	16	-	mV
			$R_f = 120\Omega$	-	60	-	mV
Input Sensitivity	$V_{i(\text{rms})}$	$P_O = 50\text{W}, V_S = 9\text{V}, f = 1\text{kHz}, R_L = 8\Omega$	$R_f = 33\Omega$	-	3.5	-	mV
			$R_f = 120\Omega$	-	12	-	mV
Input Resistance	$R_i$		-	5	-	MΩ	
Frequency Response (-3dB)	B	$V_S = 9\text{V}, R_L = 8\Omega, R_f = 120\Omega$	$C_B = 680\text{pF}$	25 to 7000		Hz	
			$C_B = 220\text{pF}$	25 to 20000		Hz	
Distortion	d	$P_O = 500\text{mW}, V_S = 9\text{V}, f = 1\text{kHz}, R_L = 8\Omega$	$R_f = 33\Omega$	-	0.8	-	%
			$R_f = 120\Omega$	-	0.4	-	%
Voltage Gain (Open Loop)	$G_V$	$V_S = 9\text{V}, f = 1\text{kHz}, R_L = 8\Omega$	-	75	-	dB	
Voltage Gain (Closed Loop)	$G_V$	$V_S = 9\text{V}, f = 1\text{kHz}, R_L = 8\Omega$	$R_f = 33\Omega$	-	45	-	dB
			$R_f = 120\Omega$	-	34	-	dB
Input Noise Voltage	$e_N$	$V_S = 9\text{V}, B = 22\text{Hz to } 22\text{kHz}$	-	3	-	$\mu\text{V}$	
Input Noise Current	$i_N$		-	0.4	-	nA	
Signal-to-Noise Ratio	$\frac{S+N}{N}$	$V_S = 9\text{V}, P_O = 1.2\text{W}, R_f = 120\Omega, R_1 = 100\text{k}\Omega, B = 22\text{Hz to } 22\text{kHz}$	-	70	-	dB	
Supply Voltage Rejection	SVR	$V_S = 9\text{V}, R_L = 8\Omega, R_f = 120\Omega, f(\text{ripple}) = 100\text{Hz}, C_6 = 50\mu\text{F}$	-	42	-	dB	

**Pin Connection Diagram**



